# Starfood, Presentation of articles

## Set up instructions for a machine that is currently in use and not loaded via the intelligent method.

Presentation of full compartments to the front of the machine takes place every 60 seconds after the shelves have been shopped round and items are not fully displayed to the front of the machine.

This will only be effective if either all compartments are filled on each loading of the machine, or the machine is loaded via the intelligent loading method following all shelves being seen as completely empty by the processor.

1. Open warm door
2. Press Programming twice
3. Press top button to scroll to tech 5 miscellaneous
4. Press Enter
5. Scroll to 5.2 - initialise D.B.
6. Press Enter twice to return to defaults
7. Press program twice
8. Scroll to prog parameters
9. Press Enter = “Cash”
10. Press Enter – Scroll to “Coin Mechanism”
11. Press Enter twice = “Validator”
12. Scroll to “Executive”
13. Press Enter, close and open warm door
14. Set prices with warm door open
15. Press Selection Button corresponding to product to be loaded
16. Load product, press selection button for next product to be loaded, continue for all drums
17. Close warm door